



## Trove2BV2 (Enclosure & Backplane) / TBV2 (Backplane)

Access and Power Integration Solutions

Trove2BV2 consists of a high-capacity enclosure with removable backplane. This unit easily combines Brivo ACS6000 boards with various Altronix power/accessories in a streamlined package. Trove simplifies board layout and wire management, reducing installation time and labor costs.



Trove2BV2

*Boards are not included*

### Trove2BV2 (Trove2 Enclosure + TBV2 Backplane) Features

- Trove2BV2 and TBV2 accommodate Brivo boards with or without Altronix power/accessories.
- One (1) ACS6000-MBE
- Up to three (3) ACS6000-DB or ACS6000-I/O
- Altronix Power Supplies and Sub-Assemblies
- Includes Altronix Trove2 Enclosure and one (1) removable TBV2 backplane

#### Agency Listings

##### UL:

UL294 - Access Control System.

##### cUL:

CAN/ULC - s319-05 - Electronic Access Control Systems.

CE European Conformity

#### Features

- Simplifies board layout and wire management
- Convenient knockout configuration:
- One (1) single knockout 2.415" (2" Conduit).

#### Features (cont'd)

- Sixteen (16) double knockouts  
1.362" (1" Conduit) / 1.115" (3/4" Conduit).
- Accommodates up to two (2) 12VDC/12AH batteries
- 16 AWG powder coated steel
- Includes cam lock, tamper switch and mounting hardware

#### Trove2BV2 - Dimensions (H x W x D):

27.25" x 21.75" x 6.5" (692.2mm x 546.1mm x 165.1mm)

#### Trove2BV2 - Weights:

Product - 37.1 lbs. (16.83 kg)  
Shipping - 40.85 lbs. (18.53 kg)

#### TBV2 - Dimensions (H x W x D):

25.375" x 19.375" x 0.3125" (644.5mm x 492.1mm x 8mm)

#### TBV2 - Weights:

Product - 8.0 lbs. (3.63 kg)  
Shipping - 10.0 lbs. (4.53 kg)

*All registered trademarks are property of their respective owners.*

**Access Controller Position Chart for the Following Models:**

Altronix / Brivo	Pem Mounting
eFlow4NB, eFlow6NB, eFlow102NB, eFlow104NB, Tango1B	(A)
ACM4, ACM4CB, LINQ8PD, LINQ8PDCB, MOM5, PD4UL, PD4ULCB, PD8UL, PD8ULCB, PDS8, PDS8CB, VR6	(B)
ACM8, ACM8CB, ACMS8, ACM8SCB, LINQ8ACM, LINQ8ACMCB	(C)
ACS6000-MBE	(D)
ACS6000-DB, ACS6000-I/O	(E)



